

ANSI X12 version 4010 864 Text Message

VERSION: 1.0 FINAL

Author:	Superior Essex
Publication Date:	08/22/00
Trading Partner:	All Partners

864

Text Message

Functional Group=TX

This Draft Standard for Trial Use contains the format and establishes the data content of the Text Message Transaction Set (864) for use within the context of an Electronic Data Interchange (EDI) environment. The transaction set can be used to provide users with a capability to electronically move messages, contracts, explanations, and other one-time communications. It is the intent of this transaction set to provide electronic communication (messages) for people, not for computer processing. The use of the transaction set to transmit quasi or unique transaction set standards is discouraged. The use of the Text Message transaction set demands of the sender certain detailed information about the recipient. The transaction set's purpose is to provide communication to the recipient in some human-readable form. The recipient's network will dictate what capabilities are available for delivery of the information. It is the responsibility of the sender to obtain this information and include it in the transmission.

Segments:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Notes</u>	<u>Usage</u>
	ISA	Interchange Control Header	M	1			Used
	GS	Functional Group Header	M	1			Used

Heading:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Notes</u>	<u>Usage</u>
010	ST	Transaction Set Header	M	1			Must use
020	BMG	Beginning Segment For Text Message	M	1			Must use
030	DTM	Date/Time Reference	O	10			Used

<u>LOOP ID - N1</u>			<u>200</u>				
040	N1	Name	O	1			Used
050	N2	Additional Name Information	O	2			Used
060	N3	Address Information	O	2			Used
070	N4	Geographic Location	O	1			Used
090	PER	Administrative Communications Contact	O	3			Used

Detail:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Notes</u>	<u>Usage</u>
------------	-----------	---------------------	------------	----------------	---------------	--------------	--------------

<u>LOOP ID - MIT</u>			<u>≥1</u>				
010	MIT	Message Identification	M	1			Must use
080	MSG	Message Text	M	10000			Must use
				0			

Summary:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Notes</u>	<u>Usage</u>
010	SE	Transaction Set Trailer	M	1			Must use

Segments:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Notes</u>	<u>Usage</u>
	GE	Functional Group Trailer	M	1			Used
	IEA	Interchange Control Trailer	M	1			Used

ISA Interchange Control Header

Pos:	Max: 1
- Mandatory	
Loop: N/A	Elements: 16

To start and identify an interchange of zero or more functional groups and interchange-related control segments

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
ISA01	I01	Authorization Information Qualifier Description: Code to identify the type of information in the Authorization Information	M	ID	2/2	Must use
		<u>Code</u> <u>Name</u>				
		00 No Authorization Information Present (No Meaningful Information in I02)				
ISA02	I02	Authorization Information Description: Information used for additional identification or authorization of the interchange sender or the data in the interchange; the type of information is set by the Authorization Information Qualifier (I01)	M	AN	10/10	Must use
ISA03	I03	Security Information Qualifier Description: Code to identify the type of information in the Security Information	M	ID	2/2	Must use
		<u>Code</u> <u>Name</u>				
		00 No Security Information Present (No Meaningful Information in I04)				
ISA04	I04	Security Information Description: This is used for identifying the security information about the interchange sender or the data in the interchange; the type of information is set by the Security Information Qualifier (I03)	M	AN	10/10	Must use
ISA05	I05	Interchange ID Qualifier Description: Qualifier to designate the system/method of code structure used to designate the sender or receiver ID element being qualified	M	ID	2/2	Must use
		<u>Code</u> <u>Name</u>				
		01 Duns (Dun & Bradstreet)				
		09 X.121 (CCITT)				
		12 Phone (Telephone Companies)				
		ZZ Mutually Defined				
ISA06	I06	Interchange Sender ID Description: Identification code published by the sender for other parties to use as the receiver ID to route data to them; the sender always codes this value in the sender ID element	M	AN	15/15	Must use
ISA07	I05	Interchange ID Qualifier Description: Qualifier to designate the system/method of code structure used to designate the sender or receiver ID element being qualified	M	ID	2/2	Must use
		<u>Code</u> <u>Name</u>				
		12 Phone (Telephone Companies)				
ISA08	I07	Interchange Receiver ID Description: Identification code published by the receiver of the data; When sending, it is used by the sender as their sending ID, thus other parties sending to them will use this as a receiving ID to route data to them	M	AN	15/15	Must use

User Note 1: 2194614000 Production
2194614462 Test



08/22/00

Text Message - 864

ISA09	I08	Interchange Date Description: Date of the interchange	M	DT	6/6	Must use
ISA10	I09	Interchange Time Description: Time of the interchange	M	TM	4/4	Must use
ISA11	I10	Interchange Control Standards Identifier Description: Code to identify the agency responsible for the control standard used by the message that is enclosed by the interchange header and trailer All valid standard codes are used.	M	ID	1/1	Must use
ISA12	I11	Interchange Control Version Number Description: This version number covers the interchange control segments <u>Code</u> <u>Name</u> 00401 Draft Standards for Trial Use Approved for Publication by ASC X12 Procedures Review Board through October 1997	M	ID	5/5	Must use
ISA13	I12	Interchange Control Number Description: A control number assigned by the interchange sender	M	N0	9/9	Must use
ISA14	I13	Acknowledgment Requested Description: Code sent by the sender to request an interchange acknowledgment (TA1) <u>Code</u> <u>Name</u> 0 No Acknowledgment Requested	M	ID	1/1	Must use
ISA15	I14	Usage Indicator Description: Code to indicate whether data enclosed by this interchange envelope is test, production or information <u>Code</u> <u>Name</u> P Production Data T Test Data	M	ID	1/1	Must use
ISA16	I15	Component Element Separator Description: Type is not applicable; the component element separator is a delimiter and not a data element; this field provides the delimiter used to separate component data elements within a composite data structure; this value must be different than the data element separator and the segment terminator	M		1/1	Must use

GS

Functional Group Header

Pos:	Max: 1
- Mandatory	
Loop: N/A	Elements: 8

To indicate the beginning of a functional group and to provide control information

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
GS01	479	Functional Identifier Code Description: Code identifying a group of application related transaction sets	M	ID	2/2	Must use
		<u>Code Name</u> TX Text Message (864)				
GS02	142	Application Sender's Code Description: Code identifying party sending transmission; codes agreed to by trading partners	M	AN	2/15	Must use
GS03	124	Application Receiver's Code Description: Code identifying party receiving transmission. Codes agreed to by trading partners	M	AN	2/15	Must use
GS04	373	Date Description: Date expressed as CCYYMMDD	M	DT	8/8	Must use
GS05	337	Time Description: Time expressed in 24-hour clock time as follows: HHMM, or HHMMSS, or HHMMSSD, or HHMMSSDD, where H = hours (00-23), M = minutes (00-59), S = integer seconds (00-59) and DD = decimal seconds; decimal seconds are expressed as follows: D = tenths (0-9) and DD = hundredths (00-99)	M	TM	4/8	Must use
GS06	28	Group Control Number Description: Assigned number originated and maintained by the sender	M	N0	1/9	Must use
GS07	455	Responsible Agency Code Description: Code used in conjunction with Data Element 480 to identify the issuer of the standard	M	ID	1/2	Must use
		<u>Code Name</u> X Accredited Standards Committee X12				
GS08	480	Version / Release / Industry Identifier Code Description: Code indicating the version, release, subrelease, and industry identifier of the EDI standard being used, including the GS and GE segments; if code in DE455 in GS segment is X, then in DE 480 positions 1-3 are the version number; positions 4-6 are the release and subrelease, level of the version; and positions 7-12 are the industry or trade association identifiers (optionally assigned by user); if code in DE455 in GS segment is T, then other formats are allowed	M	AN	1/12	Must use
		<u>Code Name</u> 004010 Draft Standards Approved for Publication by ASC X12 Procedures Review Board through October 1997				

Semantics:

- GS04 is the group date.
- GS05 is the group time.
- The data interchange control number GS06 in this header must be identical to the same data element in the associated functional group trailer, GE02.

Comments:

- A functional group of related transaction sets, within the scope of X12 standards, consists of a collection of similar transaction sets enclosed by a functional group header and a functional group trailer.

ST Transaction Set Header

Pos: 010	Max: 1
Heading - Mandatory	
Loop: N/A	Elements: 2

To indicate the start of a transaction set and to assign a control number

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
ST01	143	Transaction Set Identifier Code Description: Code uniquely identifying a Transaction Set	M	ID	3/3	Must use
		<u>Code Name</u> 864 Text Message				
ST02	329	Transaction Set Control Number Description: Identifying control number that must be unique within the transaction set functional group assigned by the originator for a transaction set	M	AN	4/9	Must use

Semantics:

- The transaction set identifier (ST01) used by the translation routines of the interchange partners to select the appropriate transaction set definition (e.g., 810 selects the Invoice Transaction Set).

BMG Beginning Segment For Text Message

Pos: 020	Max: 1
Heading - Mandatory	
Loop: N/A	Elements: 2

To indicate the beginning of a Text Message Transaction Set

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
BMG01	353	Transaction Set Purpose Code Description: Code identifying purpose of transaction set	M	ID	2/2	Must use
		<u>Code Name</u> 00 Original				
BMG02	352	Description Description: A free-form description to clarify the related data elements and their content	O	AN	1/80	Used

Comments:

- BMG02 contains the message subject.

DTM Date/Time Reference

Pos: 030	Max: 10
Heading - Optional	
Loop: N/A	Elements: 6

To specify pertinent dates and times

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
DTM01	374	Date/Time Qualifier Description: Code specifying type of date or time, or both date and time All valid standard codes are used.	M	ID	3/3	Must use
DTM02	373	Date Description: Date expressed as CCYYMMDD	C	DT	8/8	Used
DTM03	337	Time Description: Time expressed in 24-hour clock time as follows: HHMM, or HHMMSS, or HHMMSSD, or HHMMSSDD, where H = hours (00-23), M = minutes (00-59), S = integer seconds (00-59) and DD = decimal seconds; decimal seconds are expressed as follows: D = tenths (0-9) and DD = hundredths (00-99)	C	TM	4/8	Used
DTM04	623	Time Code Description: Code identifying the time. In accordance with International Standards Organization standard 8601, time can be specified by a + or - and an indication in hours in relation to Universal Time Coordinate (UTC) time; since + is a restricted character, + and - are substituted by P and M in the codes that follow All valid standard codes are used.	O	ID	2/2	Used
DTM05	1250	Date Time Period Format Qualifier Description: Code indicating the date format, time format, or date and time format All valid standard codes are used.	C	ID	2/3	Used
DTM06	1251	Date Time Period Description: Expression of a date, a time, or range of dates, times or dates and times	C	AN	1/35	Used

Syntax:

1. DTM02 R020305 -- At least one of DTM02, DTM03 or DTM05 is required.
2. DTM04 C0403 -- If DTM04 is present, then DTM03 is required
3. DTM05 P0506 -- If either DTM05 or DTM06 are present, then the others are required.

N1**Name**

Pos: 040	Max: 1
Heading - Optional	
Loop: N1	Elements: 4

To identify a party by type of organization, name, and code

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
N101	98	Entity Identifier Code Description: Code identifying an organizational entity, a physical location, property or an individual All valid standard codes are used.	M	ID	2/3	Must use
N102	93	Name Description: Free-form name	C	AN	1/60	Used
N103	66	Identification Code Qualifier Description: Code designating the system/method of code structure used for Identification Code (67) All valid standard codes are used.	C	ID	1/2	Used
N104	67	Identification Code Description: Code identifying a party or other code	C	AN	2/80	Used

Syntax:

1. N102 R0203 -- At least one of N102 or N103 is required.
2. N103 P0304 -- If either N103 or N104 are present, then the others are required.

Comments:

1. This segment, used alone, provides the most efficient method of providing organizational identification. To obtain this efficiency the "ID Code" (N104) must provide a key to the table maintained by the transaction processing party.
2. N105 and N106 further define the type of entity in N101.

N2**Additional Name Information**

Pos: 050	Max: 2
Heading - Optional	
Loop: N1	Elements: 2

To specify additional names or those longer than 35 characters in length

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
N201	93	Name Description: Free-form name	M	AN	1/60	Must use
N202	93	Name Description: Free-form name	O	AN	1/60	Used

N3**Address Information**

Pos: 060	Max: 2
Heading - Optional	
Loop: N1	Elements: 2

To specify the location of the named party

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
N301	166	Address Information Description: Address information	M	AN	1/55	Must use
N302	166	Address Information Description: Address information	O	AN	1/55	Used

N4

Geographic Location

Pos: 070	Max: 1
Heading - Optional	
Loop: N1	Elements: 4

To specify the geographic place of the named party

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
N401	19	City Name Description: Free-form text for city name	O	AN	2/30	Used
N402	156	State or Province Code Description: Code (Standard State/Province) as defined by appropriate government agency	O	ID	2/2	Used
N403	116	Postal Code Description: Code defining international postal zone code excluding punctuation and blanks (zip code for United States)	O	ID	3/15	Used
N404	26	Country Code Description: Code identifying the country	O	ID	2/3	Used

Syntax:

1. N406 C0605 -- If N406 is present, then N405 is required

Comments:

1. A combination of either N401 through N404, or N405 and N406 may be adequate to specify a location.
2. N402 is required only if city name (N401) is in the U.S. or Canada.

PER Administrative Communications Contact

Pos: 090	Max: 3
Heading - Optional	
Loop: N1	Elements: 6

To identify a person or office to whom administrative communications should be directed

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
PER01	366	Contact Function Code Description: Code identifying the major duty or responsibility of the person or group named All valid standard codes are used.	M	ID	2/2	Must use
PER02	93	Name Description: Free-form name	O	AN	1/60	Used
PER03	365	Communication Number Qualifier Description: Code identifying the type of communication number All valid standard codes are used.	C	ID	2/2	Used
PER04	364	Communication Number Description: Complete communications number including country or area code when applicable	C	AN	1/80	Used
PER05	365	Communication Number Qualifier Description: Code identifying the type of communication number All valid standard codes are used.	C	ID	2/2	Used
PER06	364	Communication Number Description: Complete communications number including country or area code when applicable	C	AN	1/80	Used

Syntax:

1. PER03 P0304 -- If either PER03 or PER04 are present, then the others are required.
2. PER05 P0506 -- If either PER05 or PER06 are present, then the others are required.
3. PER07 P0708 -- If either PER07 or PER08 are present, then the others are required.

MIT

Message Identification

Pos: 010	Max: 1
Detail - Mandatory	
Loop: MIT	Elements: 4

To identify the beginning of a specific message and to allow the identification of a subject for the message

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
MIT01	127	Reference Identification Description: Reference information as defined for a particular Transaction Set or as specified by the Reference Identification Qualifier	M	AN	1/30	Must use
MIT02	352	Description Description: A free-form description to clarify the related data elements and their content	O	AN	1/80	Used
MIT03	931	Page Width Description: Definition of the maximum number of characters per line that can be expected in the message text	O	N0	1/3	Used
MIT04	932	Page Length Lines Description: Definition of the maximum number of lines per page that can be expected in the message text	O	N0	1/3	Used

Semantics:

1. MIT01 contains the message number.
2. MIT02 contains the message subject.

Comments:

1. MIT03 default is 80 characters.
2. MIT04 default is 66 lines.

MSG Message Text

Pos: 080	Max: 100000
Detail - Mandatory	
Loop: MIT	Elements: 3

To provide a free-form format that allows the transmission of text information

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
MSG01	933	Free-Form Message Text Description: Free-form message text	M	AN	1/264	Must use
MSG02	934	Printer Carriage Control Code Description: A field to be used for the control of the line feed of the receiving printer All valid standard codes are used.	C	ID	2/2	Used
MSG03	1470	Number Description: A generic number	O	N0	1/9	Used

Syntax:

1. MSG03 C0302 -- If MSG03 is present, then MSG02 is required

Semantics:

1. MSG03 is the number of lines to advance before printing.

Comments:

1. MSG02 is not related to the specific characteristics of a printer, but identifies top of page, advance a line, etc.
2. If MSG02 is "AA - Advance the specified number of lines before print" then MSG03 is required.

SE

Transaction Set Trailer

Pos: 010	Max: 1
Summary - Mandatory	
Loop: N/A	Elements: 2

To indicate the end of the transaction set and provide the count of the transmitted segments (including the beginning (ST) and ending (SE) segments)

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
SE01	96	Number of Included Segments Description: Total number of segments included in a transaction set including ST and SE segments	M	N0	1/10	Must use
SE02	329	Transaction Set Control Number Description: Identifying control number that must be unique within the transaction set functional group assigned by the originator for a transaction set	M	AN	4/9	Must use

Comments:

- SE is the last segment of each transaction set.

GE

Functional Group Trailer

Pos:	Max: 1
- Mandatory	
Loop: N/A	Elements: 2

To indicate the end of a functional group and to provide control information

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
GE01	97	Number of Transaction Sets Included Description: Total number of transaction sets included in the functional group or interchange (transmission) group terminated by the trailer containing this data element	M	N0	1/6	Must use
GE02	28	Group Control Number Description: Assigned number originated and maintained by the sender	M	N0	1/9	Must use

Semantics:

- The data interchange control number GE02 in this trailer must be identical to the same data element in the associated functional group header, GS06.

Comments:

- The use of identical data interchange control numbers in the associated functional group header and trailer is designed to maximize functional group integrity. The control number is the same as that used in the corresponding header.

IEA

Interchange Control Trailer

Pos:	Max: 1
- Mandatory	
Loop: N/A	Elements: 2

To define the end of an interchange of zero or more functional groups and interchange-related control segments

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
IEA01	I16	Number of Included Functional Groups Description: A count of the number of functional groups included in an interchange	M	N0	1/5	Must use
IEA02	I12	Interchange Control Number Description: A control number assigned by the interchange sender	M	N0	9/9	Must use